

Market Central^O www.secureswitch.com

CAT6 RJ45 MANUAL SWITCHES

January 2020

FRONT PANEL VIEW



1. Specifications:

Connectors:

(3) CAT6 RJ45 - 2 to 1 (A/B/C Switch) (4) CAT6 RJ45 - 3 to 1 (A/B/C/D Switch) (5) CAT6 RJ45 - 4 to 1 (A/B/C/D/E Switch)

Compliance: meets CAT6 requirements for 10GBase-T Ethernet networks

Data Rates:

Transparent to data rates, signal levels, formats, and protocols. Support 10/100/1000 Mbit, and 10 Gbit Ethernet.

Mean Time Between Failures: 100,000 cycles.

Operating Temperature: 32 to 158°F (0 to 70°C)

Relative Humidity Tolerance: up to 95%, non-condensing

Power: Non-powered

Size: 2.75"H x 6.1"W x 6.5"D (desktop models) 1.74"H x 19"W x 5"D (rackmount A/B model)

Weight: 2.0 lbs.

2. Introduction:

These high performance CAT6 RJ45 switches use push-button style selector switches and Category 6 connectors to ensure reliable operation and accurate communications of high speed Ethernet signals between the "C" (common) port and the selected port.

3. Installation:

Locate the switch in a stable environment that is relatively free of vibration and contamination. No external power is required to operate the switch. Ethernet cables that conform to the speed of the data to be passed through the switch should be used for all connections.

Connect your host device (or shared network connection) to port C (COMMON port). Connect the different networks or Ethernet devices to the A, B (and D and E) ports on the switch. Depress the front panel push-button selector switch(es) to create a connection between port C (the COMMON port) and the desired network port.

Your installation of this switch is now complete.

4. Operation:

Operate the switch by following the diagram on the face plate of the unit to select the port that you wish to connect to the "C" (common) port.. Each push-button switch has an IN and an OUT position. The indicator on the button is white when the push-button switch is pushed IN, and black when it is in the OUT position.

Note that all possible positions for the push-button switches are not shown on the faceplate silkscreens for the A/B/C/D and the A/B/C/D/E Switches. For example, if the A/B/C/D Switch is set with the left push-button IN and the right push-button OUT, this will also connect the Common port to port A (same as both push-buttons OUT). This alternate way to select port A can be used, but is not shown to help minimize confusion.

Likewise, the A/B/C/D/E Switch has 4 additional push-button settings that are not shown on the faceplate silkscreen. These redundant positions and the port selected are: OUT/IN/IN - E, IN/OUT/OUT - B, IN/OUT/IN - A, and IN/IN/IN - D.

MARKET CENTRAL, INC.

WARRANTY AND LIMITATION OF LIABILITY

Market Central, Inc. ("Market Central") warrants that the products manufactured and sold by it or by one of its authorized resellers will, when sold, be free of defects in workmanship or material under normal service and use. Products which have been changed or altered in any manner from their original design, or which are improperly or defectively installed, serviced or used, are not covered by this warranty. If any failure to conform to this warranty becomes apparent during a period of one year after date of sale, Market Central shall, upon prompt, written notice and compliance by the customer with such instructions as it shall give with respect to the return of defective products or parts, correct such non-conformity by repair or replacement of the defective part of parts. Correction in the manner provided above shall constitute a complete fulfillment of all obligations and liabilities of Market Central with respect to the quality of said products. THE FOREGOING WARRANTY IS EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES OF QUALITY, WHETHER WRITTEN, ORAL OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR PURPOSE.

THIS WARRANTY AND THE OBLIGATIONS AND LIABILITIES OF MARKET CENTRAL HEREUNDER ARE EXCLUSIVE AND IN LIEU OF AND BUYER HEREBY WAIVES ALL OTHER REMEDIES, WARRANTIES, GUARANTIES OR LIABILITIES, EXPRESS OR IMPLIED, ARISING BY LAW OR OTHERWISE (INCLUDING WITHOUT LIMITATION ANY OBLIGATIONS OF MARKET CENTRAL WITH RESPECT TO FITNESS FOR PURPOSE, MERCHANTABILITY AND INDIRECT, SPECIAL OR CONSEQUENTIAL DAMAGES OR LOST PROFITS) OR WHETHER OR NOR OCCASIONED BY MARKET CENTRAL'S NEGLIGENCE. THIS WARRANTY SHALL NOT BE EXTENDED, ALTERED OR VARIED EXCEPT BY A WRITTEN INSTRUMENT SIGNED BY A DULY AUTHORIZED OFFICER OF MARKET CENTRAL.